PowerTech [™] EWX 4045TFC03 Diesel Engine







General data			
Model	4045TFC03	Length - mm (in)	870 (34.3)
Number of cylinders	4	Width - mm (in)	720 (28.3)
Displacement - L (cu in)	4.5 (275)	Height mm (in)	960 (37.8)
Bore and Stroke mm (in)	106 x 127 (4.17 x 5.00)	Weight, dry - kg (lb)	510 (1124)
Compression Ratio	19.0 : 1		
Engine Type	In-line, 4-cycle		
Aspiration	Turbocharged		

Continuous	
55 kW(74 hp) @2200-2400rpm	
55 kW (74 hp) @2200-2400rpm	
0% @ NA rpm	
304 N.m (224ft-lb) @1600rpm	
39%	

The Industrial Continuous engine power rating is for applications that operate with constant load and speed, except for short periods during startup or shutdown. Power output is within + or - 5% at standard SAE J 1995 and ISO 3046.

DOC/DPF Dimensions

Size	2
Diameter - mm (in)	209 (8.2)
Length - mm (in)	573 (22.6)
Weight - kg (lb)	20 (44.1)

See your John Deere Power Systems engine distributor for more information on available filter size options.

Features and Benefits

Ready to Run. Stage V.

- John Deere is ready to work, ready to generate, and ready to run with engines meeting

EU Stage V emissions regulations. This means OEM customers currently using a John Deere engine with a diesel particulate filter (DPF) won't have to re-engineer their machine to meet the requirements of Stage V regulations. John Deere has been using DPF technology since Interim Tier 4/Stage III B, and is well positioned to help customers transition to the EU's Stage V standard. We have extensive experience with the development and integration of DPFs in both John Deere and OEM equipment, with more than 425 million DPF hours in the field.*

Wastegated Turbocharger

- Wastegated turbochargers are designed to develop more airflow at lower

engine speeds to improve low-speed torque. The wastegate control device bleeds off a portion of the exhaust flow at higher engine speeds. Wastegated turbos deliver improved transient response and higher peak torque without compromising engine envelope size. They also provide the lowest installed cost across a given power range.

Exhaust Filters

- These engines utilize a catalyzed exhaust filter that contains a diesel

oxidation catalyst (DOC) and a diesel particulate filter (DPF). The DOC reacts with exhaust gases to reduce carbon monoxide, hydrocarbons, and some particulate matter (PM). The downstream DPF traps and holds the remaining PM. Trapped particles are oxidized within the DPF through a continuous cleaning process called passive regeneration. Passive regeneration occurs during normal operating conditions when heat from the exhaust stream and catalysts within the exhaust filter trigger the oxidation of the trapped PM. If passive regeneration cannot be achieved due to low temperature, load, or speed, then PM is removed using active regeneration — an automatic cleaning process controlled by the exhaust temperature management system.

High-Pressure Common-Rail (HPCR) and Engine Control Unit (ECU)

 The HPCR fuel system provides variable common-rail pressure and higher injection pressures up to 1,600 bar (23,000 psi). It also controls fuel injection timing and provides precise control for the start, duration, and end of injection.

2-Valve Cylinder Head

- Cross-flow head design provides excellent breathing from a lower-cost 2valve cylinder head.

Turbocharged

 In turbocharged engines, the air is precompressed. Due to the higher pressure, more air is supplied into the combustion chamber, allowing a corresponding increase in fuel injection, which results in greater engine output.

John Deere Power Systems 3801 W. Ridgeway Ave. PO Box 5100 Waterloo, IA 50704-5100 Phone: 1-800-533-6446 Fax: 319.292.5075

John Deere Power Systems Usine de Saran La Foulonnerie - B.P. 11.13 45401 Fleury les Aubrais Cedex France Phone: 33.2.38.82.61.19

Fax: 33.2.38.82.60.00

All values at rated speed and power with standard options unless otherwise noted. Specifications and design subject to change without notice.

